

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)

Bus system connector, 5-position, shielded, Plug angled M12, B-coded, Spring-cage connection, Knurl material: Nickel-plated brass, External cable diameter 4 mm ... 8 mm



Why buy this product

- Safe use in the field, thanks to a high degree of protection
- Flexible: connectors for on-site assembly
- Spring-cage connection: connect more securely, even in the case of shock and vibration, thanks to high contact forces
- Reliable signal transmission 360° shielding in environments with electromagnetic interference



Key Commercial Data

Packing unit	1 STK
GTIN	4 046356 149068
GTIN	4046356149068

Technical data

Dimensions

External diameter	4 mm 8 mm
Stripping length of the sheath	35 mm
Stripping length of the individual wire	10 mm

Ambient conditions

Ambient temperature (operation)	-40 °C 85 °C (Plug / socket)
Degree of protection	IP67

General

Rated current at 40°C	4 A
Rated voltage	60 V DC
	48 V AC
Number of positions	5



Technical data

General

\geq 100 M Ω		
B-coded		
M12 connector IEC 61076-2-101		
No		
11		
3		
Spring-cage connection		
0.14 mm ² 0.5 mm ²		
26 20		
≥ 100		
0.4 Nm (M12 knurl)		
0.8 Nm (Connector with coupling sleeve)		
3 Nm (Pressure nut)		
The connector pin assignment can be rotated 45° to the cable outlet		
The wires can be connected both with ferrules and without ferrules		

Material

Flammability rating according to UL 94	V0
Contact material	CuSn
Contact surface material	Ni/Au
Contact carrier material	PA 66
Material of grip body	Zinc die-cast, nickel-plated
Material, knurls	Nickel-plated brass
Sealing material	NBR

Standards and Regulations

Standard designation	M12 connector
Standards/regulations	IEC 61076-2-101
Connection in acc. with standard	CUL
Flammability rating according to UL 94	V0

Drawings



Schematic diagram




Pin assignment M12 male connector, 5-pos., B-coded, male side

Functional drawing

Slide the pressure nut and sleeve housing along the cable, strip the cable, shorten the shield, strip the single wires, connect the wires, in the case of a straight sleeve housing gently twist the wires together, stick the shielding foil around the shortened shield, in the case of a cable outside diameter < 6 mm stick an additional shielding foil around the wire pack, screw the sleeve housing to the plug insert, screw the pressure nut tight.

3 Nm



M12 x 1 male plug, angled, shielded

Approvals

Approvals

Approvals

UL Recognized / cUL Recognized / cULus Recognized

Ex Approvals



Approvals

Г

Approval details

UL Recognized	http://database.ul.cor	http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm	
Nominal current IN		4 A	
Nominal voltage UN		125 V	

cUL Recognized	C A L	http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm		FILE E 118976
Nominal current IN			4 A	
Nominal voltage UN			125 V	

cULus Recognized



http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm

Phoenix Contact 2017 © - all rights reserved http://www.phoenixcontact.com

PHOENIX CONTACT GmbH & Co. KG Flachsmarktstr. 8 32825 Blomberg Germany Tel. +49 5235 300 Fax +49 5235 3 41200 http://www.phoenixcontact.com