






P.C.B. MOUNTING PLAN












## This electronic component is designed and developed with the intention for use in general electronics equipments.

Before incorporating the components into any equipments in the field such as aerospace, aviation, nuclear control, submarine, transportation, (automotive control, train control, ship control), transportation signal, disaster prevention, medical, public information network etc. where higher safety and reliability are especially required or if there is possibility of direct damage or injury to human body, Wurth Elektronik must be asked for a written approval.

In addition, even electronic component in general electronic equipments, when used in electrical circuits that require high safety, reliability functions or performance, the sufficient reliability evaluation-check for the safety must be performed before by the user before usage.



					Date	Name	
				Drawn	09-09-14	Jelisa	
е	remove Contact cladding	14-11-03	DaF	Checked	09-09-14	Hsu	
d	revised MatchCode	14-07-24	AL				
С	Bounce 10ms max.	14-04-11	DaF	WE	Würth Elektronik		
b	washable definition	14-1-31	DaF	eiCan CAD			
а	warning text	11-10-28	WJ	(CAD)	elCan		
REV	FILE	DATE	BY	EDV NO	4304x3xxx	8x6.dft	

Scale Drawing.- No. 4304x3xxx8x6

5:1

WS-TASV 6x6mm washable Tact Switch, J-Bend SMD version

Position SIZE A4

System: Solid Edge V20

**SPECIFICATION** >Rating:

TECHNICAL CHARACTERISTICS

50mA. 12VDC >Contact Resistance:

Initial: 100mOHM max. After Life Test: 20HM max. >Insulation Resistance: min. 100MOHM at 500VDC >Dielectric Strength: 250VAC for 1 minute >Stroke:  $0.25 + 0.2 \, \text{mm} / - 0.1 \, \text{mm}$ >Bounce 10ms max.

MATERIAL

>Cover: Stainless Steel LCP UL 94V-0 >Stem:

>Frame: LCP UL 94V-0, color Black >Contact: Stainless Steel with silver >Terminal: copper alloy with silver plating

>Tape: Polyimide tape

## **SOLDERING INFORMATION**

>Terminal in J-Bend version

>Reflow soldering according to JEDEC J-STD 020 Hot Air

>Hand soldering under 350°C for 3 sec. max

## WASHABLE DEFINITION

Please do not submerse washable products into water or cleaning agents or put them in locations exposed to water or liquids completely. When cleaning by hand (brushing), please do not use excessive force on our switch to avoid malfunction afterwards, because you could deform function relevant areas or you could damage sealing functions. Do not clean washable series immediately after soldering. The cleaning agent may be absorbed into the switch through respiration while the switch cools.

**ENVIRONMENTAL** 

>Storage condition: -40°C ~ +85°C >Operation condition: -40°C ~ +85°C >Compliance: Lead Free, ROHS, Reach

## PACKAGING INFORMATION

Basic material

**DESCRIPTION** 

>Tape & Reel

PN	Force	Color of Stem Life cycle		-025		-031		-035	
				H	ØΒ	H	ØΒ	H	ØΒ
430 483 xxx 816	160g ± 50gf	Black	1.000.000	2.5	3.0	3.1	3.0	3.5	3.0
430 473 xxx 826	260g ± 50gf	White	500.000						
430 453 xxx 836	360g ± 50gf	Salmon	200.000						