

DWG. NO. 031-3974 REVISIONS SYM. E.C.O. DATE APVD.

A 27892 3/24/14


REDRAWN TO CAD

2.62 [66.7] DIA. KNOB





.38 [9.5] DIA. SHAFT →




<u>FIGURE A</u> MAXIMUM OUTPUT CURRENT OF ANY DUAL INPUT VOLTAGE OR VOLTAGE DOUBLER UNIT OPERATED AT LOWER INPUT VOLTAGE.

- # MAXIMUM OUTPUT CURRENT IN OUTPUT VOLTAGE RANGE FROM 0 TO 25% ABOVE LINE VOLTAGE. AT HIGHER OUTPUT VOLTAGES, THE OUTPUT CURRENT MUST BE REDUCED ACCORDING TO THE DERATING CURVE FIGURE A.
- § MAXIMUM KVA AT MAXIMUM OUTPUT VOLTAGE AND CORRESPONDING DERATED OUTPUT CURRENT. MAXIMUM KVA FOR LOWER VOLTAGES MAY BE CALCULATED FROM DERATING CURVE FIGURE A.

++ LINE TO LINE VOLTAGE.

- au if ganged units are used in a system that ordinarily has a common NEUTRAL OR GROUND BETWEEN SOURCE AND LOAD, THE NEUTRAL OR GROUND MUST BE CONNECTED TO THE COMMON TERMINALS OF THE VARIABLE TRANSFORMER ASSEMBLY. IF THE SYSTEM HAS NO NEUTRAL, THE LOAD MUST BE BALANCED OR THE TRANSFORMER WILL BE DAMAGED.
- JUMPER PROVIDED IN STANDARD COMMON POSITION AND SHOULD BE MOVED OR REMOVED AS REQUIRED.

NOTE: Unit is supplied with a 3.75 [95.2] dia. 0-100 graduated dial plate for panel mounting.



<u>SCHEMATIC</u> THREE PHASE WYE FUSES RECOMMENDED BUT NOT SUPPLIED

| SPECIFICATIONS | | | | | | | | | | | | | | | |
|---|-------------|------------------------------------|--------------|----------|-----------------------------|------------|--------------|-------------------------------|----------------------|--------------------|-------------------------------|--|---|-------|--------|
| | INPUT | | | OUTPUT | | | | | | | SHAFT | TERMINAL CONNECTIONS | | | |
| WIRING | VOLTS | HERTZ | VOLTS | | CONSTANT CURRENT LOAD | | | CONSTANT IMPEDANCE LOAD | | | ROTATION TO INCREASE | FOR INCREASING VOLTAGE AS VIEWED FROM BASE END | | | |
| | | | | | | AX. 1PS | MAX. KVA | MAX. AMPS | MAX KVA | | VOLTAGE | INPL | | | OUTPUT |
| THREE PHASE WYE T | | = - / | | | | | | | | | CW | 2-2-2 | | 4-4-4 | 3-3-3 |
| | 480 ++ | 50/60 | 0-480 | | 9.5 | | 7.90 | 12 | 10 | | CCW | 4-4-4 | | 2-2-2 | 3-3-3 |
| | | C O | | 0 560 | | E | 0.01 | | | | CW | 1-1-1 | | 4-4-4 | 3-3-3 |
| | | 60 0 | | 0-560 | | .5 | 9.21 | | | | CCW | 5-5-5 | | 2-2-2 | 3-3-3 |
| | 240 | 60 | | 0-560 | | 5# | 3.96 § | | | | CW | 7-7-7 | | 4-4-4 | 3-3-3 |
| | ++ | 00 | | | | J# | 3.903 | | | | CCW | 6-6-6 | | 2-2-2 | 3-3-3 |
| UNLESS OTHERW DECIMALS F .XX .010 .06 .XXX .005 | : | UNITS IN [mm] | | | | | CONTRO | | | AWING | | STA | CO | | |
| MATERIAL : | | ALL DIMENSIONS APPLY AFTER PLATING | | | | | | () () | ANSFORMER 5200-3 | | | NER | GY. | | |
| The information and design disclosed herein was originated and is the property of STACO ENERGY PRODUCTS CO., which rese all patent, proprietary, design, manufacturing, reproduction, | | | | | rves | DRAWN - | by T.SNAY | DATE 3/2 | 3/21/14 | | RST USED ON DO NOT SCALE DWG. | | PRODUCTS CO. A Components Corporation of America Company 301 Gaddis Boulevard Dayton, Ohio 45403 USA | | |
| and sale rights except to the | dis gran | closed ther ted to othe | rein ers. | CHECKE | IR . | DATE | DATE | | ht approx. 66 LBS | cage code 83008 | DWG. SIZE | DWG. NO. | 7 0 7 4 | | |
| The foregoing | prop | orietary pa | rts. | ENGINEER | | DATE | DATE | | .50=1 | SHEET 1 OF 1 | | 031 - 1 | 59/4 | | |

