SAMSUNG		LED Module	Rev. No	Page
			1.2	1 / 13
	SPE	ECIFICATION		
-				
ي : • و نه نه نه نه نه نه نه نه نه	• مختخفت فخف ف ف فره ه	د. من به	1993 1993 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 - 1994 -	
~• <u> </u>		• • •	(Anata)	0.00
	Lin	ear Module Gen2, H-series		
	Lin	ear Module Gen2, H-series (Zhaga Compliant)		
	Lin Model Name			
		(Zhaga Compliant)		
	Model Name	(Zhaga Compliant) LT-H564A		
	Model Name Type	(Zhaga Compliant) LT-H564A 560x40x5.95[mm], 700 mA (23.2V)		
	Model Name	(Zhaga Compliant) LT-H564A 560x40x5.95[mm], 700 mA (23.2V) SI-B8V161560WW (3000K) SI-B8U161560WW (3500K) SI-B8T161560WW (4000K)		
	Model Name Type	(Zhaga Compliant) LT-H564A 560x40x5.95[mm], 700 mA (23.2V) SI-B8V161560WW (3000K) SI-B8U161560WW (3500K)		
	Model Name Type	(Zhaga Compliant) LT-H564A 560x40x5.95[mm], 700 mA (23.2V) SI-B8V161560WW (3000K) SI-B8U161560WW (3500K) SI-B8T161560WW (4000K)		
	Model Name Type Parts No.	(Zhaga Compliant) LT-H564A 560x40x5.95[mm], 700 mA (23.2V) SI-B8V161560WW (3000K) SI-B8U161560WW (3500K) SI-B8T161560WW (4000K)		



LED Module

Revision History

Rev.No	Data	Page	Revision	Remark					
1.0	luno 2 2012		The first preliminary specification is						
1.0	June 3, 2013	-	established. Total 12 pages	-					
		-	Update LED orientation in all drawings	-					
1.1	June 12, 2013	5	Add min. and max value for "Operating						
		5	Voltage"	-					
							1	Add parts no.	-
		5	Update Luminous Flux & Vf spec	-					
		6	Add color coordinate spec for all CCTs	-					
		7	Update drawing including 3 way views	-					
1.2	August 15, 2013	8	Update connection guide for parallel and serial						
		0	Update connector information	-					
			10	Add circuit schematic	-				
		11	Update CE status completed	-					
		-	Total 13 pages						

SAMSUNG	SAMSUNG LED Module		Page	
UNINOUND				
	Contents			
1	Products and Applications	4		
2	Specification	4		
3	Structure and Assembly	7		
4	Approbation	11		
5	Packing	11		
6	Precautions In Handling	12		



1. Products and Application

This specification defines general specification and performance for LED Linear module. Samsung Linear Modules target to replace conventional fluorescent lamps as T5, T8 and so on with LED solutions. Due to transferring LED, new luminaire transferred to LED can take more energy saving and longer life-time.

In special, Samsung has competitiveness in middle-power solutions. This module uses LM561B. Middle power solutions provide more homogeneous and higher efficient lights. Linear module has been designed to expand length simply and adopt easy connection way.

2. Specification

No.	Item	Specifications	Unit	Remark
2-1	Dimension	560.0(L) × 40.0(W) × 5.95(h) mm	mm	Tolerance:±0.5mm
2-2	Weight	56	g	Tolerance:±5.6g
2-3	Rated lifetime	50,000 Hr	hour	L70B50 @Tc = 65℃
2-4	Ingress Protection	N/A	-	-
2-5	Operating Temperature	Tc = - 20 ~ 70	Ĵ	-
2-6	Storage Temperatue	Ta = - 35 ~ 85	Ĵ	-


SAMSUNG


LED Module

No.	Item			Unit	Remark								
INO.	nem	Sym.	Model	Min.	Nom.	Max.		Kennark					
								3000K	1990	2140	2400		
2-7	Luminous flux	Φν	3500K	2030	2200	2440	- Im	@700mA, 23.2V					
2-1		Ψ_{v}	4000K	2100	2280	2500		Tc = 45℃					
			5000K	2160	2320	2600							
			3000K	-	132	-							
2-8	Efficiency	LPW	3500K	-	135	-	Im/W	@700mA, 23.2V					
2-0			4000K	-	141	-		Tc = 45℃					
			5000K	-	143	-							
						_	3	_		MacAdam			
2-9	Color consistency	-	-			_	step	@ initial time					
			-	-	5	-		@10K hrs					
2-10	Color Rendering Index	CRI	-	80	-	-	Ra	-					
			3000K	2946	3022	3099							
2-11	ССТ	_	3500K	3340	3446	3553	ĸ	@700mA, 23.2V					
			4000K	3859	3984	4109		Tc = 45℃					
			5000K	4800	5025	5251							
2-12	Operating Current	lop	-	-	700	1200	mA	-					
2-13	Operating Voltage	Vdc	_	21.9	23.2	24.9	V	@700mA,					
				21.0	20.2	21.0		Tc = 45℃					
2-14	Power Consumption	_	_	15.3	16.2	17.4	w	@700mA,					
				10.0	10.2	17.7	~ ~	Tc = 45℃					

* Measurement tolerance of luminous flux becomes \pm 7% in the value, measurement tolerance of Vf becomes \pm 0.3V in the value and the measurement tolerance of the color coordinates is \pm 0.005. SAMSUNG

LED Module





* Measurement tolerance of luminous flux becomes \pm 7% in the value, measurement tolerance of Vf becomes \pm 0.3V in the value and the measurement tolerance of the color coordinates is \pm 0.005.

SAMSUNG		LED Mod	ulo	Rev. No	Page	
ANISONO.			uie	1.2	7 / 13	
Structure and Assembly						
3-1. Appearance						
	ہ . خ خ خ خ ہ	و و توقیق و و و و و و و و و و و و و و و و	LT-8554 (Collection) Ren 👷 👷	(1) ())))		
•		÷ • •			• •	
		<top view=""></top>				
-2. Drawing a	& Dim	ension				
		560.0		0		
				15.0 15.0		
					40 0	
	\$					
	\$					
	\$					
	\$					
	\$				20 U U U	
	\$					
	\$		<u>10</u>			
		110 .0 61.0 110				
		110 .0 61.0 110	Specifications 560.0 ± 0.5 mm			
	L	110 .0 61.0 110	Specifications 560.0 ± 0.5 mm 40.0 ± 0.3 mm			


SAMSUNG	Module	Rev. No	Pag
	Module	1.2	8 / 1

ge 13


3-3. Assembly

This module adapts terminal strip connection method to connect between LED modules like as below.


- Parallel Connection



- Serial Connection



- Connector : Terminal strip type



AWG 24-18


- (1) Insert solid conductors via push-in termination.
- (2) Insert or remove fine-standard conductors by lightly pressing on push-button.


	SAMSUNG				Rev. No	Page
	3/10/30100					
÷	3-4. Structure	9				
	•:: @:: ••• @:: •• @:'	•	د د د د د د د د د د د د د د د د د د د	LT.35544 (10000 1000) 900 کې د اورون کې	: 週 (1) (1) (1) (1) (1) (1) (1) (1) (1) (1)	
	No.		Item	Specification	S	
		3-1	LED	LM561B : Middle Power LED 64 ea		
	Module	3-2	РСВ	Material : Copper, Solder ma	ask and Epo	оху

Module	3-2	PCB	Material : Copper, Solder mask and Epoxy
Assembly	3-3	Connector	AWG 24-18 Strip Length 6-7 mm
	3-4	Resistor (NTC)	15 KΩ Nominal B-value : B (25/50) - 4110 Kelvin

3-5. Light Distribution

(1) Polar Intensity Diagram : Beam Angle 115 ± 5 [°]







4. Approbation

Item	Compliant to	Result / Remark
General	Eye safety : IEC62471	LM561B LED
Hazardous Substance &	ROHS	-
Materials	REACH	
	CE	IEC 62031:2008 IEC 62471:2008
Certification	ENEC	TBD
	UL/cUL	TBD

5. Packing

5-1 Dimension & Module Q'ty

(1) Box : 635(L) x 375(W) x 195(h) (Tolerance : ±1.5mm)

(2) Q'ty

-	1 Tray	1 Box	1 Pallet
Num. of modules	32	128	2304 (18 boxes)

(3) Pallet : 800(L) x 1200(W) x 145(h) mm



6. Precautions In Handling

1) LED Lighting for white light are devices which are materialized by combining white LEDs. The color of white light can differ a little unusually to diffuser plate(sign-board panel).

2) Handling

- Don't drop the unit and don't give the unit any shocks.
- Don't storage the Module in a dusty place or room.
- Don't take the unit to pieces.

3) Cleaning

- This LED Module should not be used in any type of fluid such as oil, organic solvent, etc.
- It is recommended that IPA(Isopropyl Alcohol) be used as a solvent for cleaning the LED Module.
- When using other solvents, it should be confirmed beforehand whether the solvents will dissolve the package and the resin or not. Freon solvents should not be used to clean the LEDs because of worldwide regulations. Do not clean the LED Module by the ultrasonic.
- Before cleaning, a pre-test should be done to confirm whether any damage to the LED Lighting will occur.

4) Static Electricity

- Static electricity or surge voltage damages the LED Lighting.
- 5) Discoloration
 - VOCs (volatile organic compounds) may be occurred by adhesives, flux, hardener or organic additives which is used in luminaires (fixture) and LED silicone bags are permeable to it. It may lead a discoloration when LED expose to heat or light.
 - This phenomenon can give a significant loss of light emitted(output) from the luminaires(fixtures).
 - In order to prevent these problems, we recommend you to know the physical properties for the materials used in luminaires, it requires to select carefully.
- 6) Risk of Sulfurization (or Tarnishing)
 - The lead frame from Samsung Electronics is a plated package and it may change to black (or dark colored) when it is exposed to Ag (a), Sulfur (S), Cchlorine (Cl) or other halogen compound. It requires attention.
 - Sulfide (Sulfurization) of the lead frame may cause a change of degradation intensity, chromaticity coordinates and it may cause open circuit in extreme cases. It requires attention.
 - Sulfide (Sulfurization) of the lead frame may cause of storage and using with oxidizing substances together. Therefore, LED is not recommend to use and store with the below list.
 Rubber, Plain paper, lead solder cream etc.

